


DJM-S3 2-CHANNEL MIXER FOR SERATO DJ

Thanks to the built-in soundcard, this 2-channel mixer is Serato DJ enabled as soon as you unpack it. Featuring a highly durable Magvel crossfader, inherited from the DJM-900NXS2, the DJM-S3 delivers a smooth and accurate response. The scratch-friendly layout creates more room for you to be creative in the booth. No need to go easy, the DJM-S3 is built to withstand intense performances. And to bring even more creativity to your performances, you can connect the DDJ-SP1 controller and use its large Performance Pads for tactile control of many Serato DJ features, including its FX.



DJM-S3

2-CHANNEL MIXER FOR SERATO DJ

PRODUCT DETAILS

KEY FEATURES

Built-in sound card

Magvel Crossfader

Independent channel filters

High Quality sound

Flexible connectivity

Two headphone output

SPECIFICATIONS

DVS control with Serato DJ

Dimensions (WxHxD) 230x108x320 mm

Weight 3 Kg

Frequency range 20 - 20000 Hz

Sampling rate 48 Hz

A/D Converter 24 bit

D/A Converter 24 bit

S/N ratio 94 dB (line)

Distortion < 0.005 % (line)

Power supply AC adaptor DC 12V

Power consumption 600 mA

EQ/ISO 3 band -8 ~ +6 dB

Channels 2

DJM-S3

2-CHANNEL MIXER FOR SERATO DJ

Sound color FX

Filter

Inputs

3 LINE (RCA), 2 PHONO (RCA), 1 MIC (1/4 inch TS Jack)

USB

1 USB B port

Outputs

1 MASTER (XLR), 1 MASTER (RCA), 2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)