

PMX-4BT

6-CHANNELS 200+200W MAX. POWERED MIXER WITH EFFECTS, MP3 AND BT


PMX-4BT is designed to be a powerful resource for live and educational purposes. The friendly user interface is one of the best features of this product and allows you to configure your sound device in a fast and easy way.

The 6-Channel Active Mixer lets you plug microphones, instruments or any other audio equipment thanks to the XLR inputs on channel 1-4, the ¼" Jack inputs on channel 1-3, the stereo RCA inputs on channel 4 and the 3mm jack input on channel 5/6 that allows you to plug in a computer, a smartphone, a tablet, etc.

Each channel features a 2- Band EQ to better tune each channel. You can also use the 3-band EQ on the master section in order to adjust the overall sound to the characteristics of the environment in which you're going to use the unit.

The system is equipped with a built-in effect with level adjustment on channels 1-4, and you can adjust master effect level, time duration and number of repeats in the FX Section.

Finally, the multimedia player with remote control reads MP3 files from the USB connector, the SD-Card slot, and the BT connection, displaying playback information through the wide LCD display.



PMX-4BT

6-CHANNELS 200+200W MAX. POWERED MIXER WITH EFFECTS, MP3 AND BT

PRODUCT DETAILS

KEY FEATURES

6-Channel 200+200W powered mixer with effect and multimedia player

4 Mic/Line channel (CH1-4) with independent 2-band EQ and FX send bus with adjustable level

1 stereo channel (CH5-6) with 3mm Jack connector for tablets, computers and other multimedia devices

3-Band EQ on Master outputs

Effect with Level, Delay Time and Repeat adjustment

RCA Stereo TAPE In/Out for an external recorder/player

MP3 player with remote control for USB, SD-Card devices and BT connection

Impact-resistant wooden enclosure with practical handle for easy transport

SPECIFICATIONS

System Type	Active Mixer with MP3 and BT Player
Rated Power	100+100W @ 4ohm
Peak Power	200+200W @ 4ohm
Frequency Range	20Hz - 20KHz +/-3dB @ 1W
Mixer	6-Channel Inputs (4 x Mono /Line, 1 x Stereo Line)
Input Impedance	Mic – 2Kohm (balanced) / 1kohm (unbalanced); Line – 10kohm / Tape IN – 47Kohm
Input Channel EQ	HIGH +/-15dB @ 12kHz; LOW +/-15dB @ 80Hz
3-Band EQ	Bass - Mid- Treble for Master Section

PMX-4BT

6-CHANNELS 200+200W MAX. POWERED MIXER WITH EFFECTS, MP3 AND BT

Stereo Monitor Out	¼" Stereo Jack (TRS)
Speaker Outputs	2x ¼" Mono Jack (TS)
Effect	Eco with Adjustable Level, Time and Repeat
Digital Delay Time	140 – 342ms
Digital Player	USB (MS-DOS® FAT-32 format, max 32GByte), SD-Card (MS-DOS® FAT-32 format, max 32GByte), Bluetooth®, LCD Display, Remote Control
AC Input	230 V – 50Hz
Fuse	T2A 250V
Unit Size	470 x 225 x 130 mm - 18.50 x 8.59 x 5.19 in
Unit Weight	7.2 Kg - 15.87 lbs.