

GO-SOUND POCKET MIC KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO- SOUND AMW SPEAKERS

The Go-Sound Pocket Mic is an optional set including a VHF bodypack transmitter, a lavalier microphone, and a headset microphone. It is intended for all of those owners of SOUNDSATION GO-SOUND AMW Active Speakers who need total freedom of movement during their sessions.



GO-SOUND POCKET MIC KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO- SOUND AMW SPEAKERS

PRODUCT DETAILS

KEY FEATURES

Compatible with GO-SOUND 8AMW / 10AMW / 12AMW / 15AMW

VHF Transmission with SMD Technology

175MHz VHF Frequency (NOTE: Before purchasing this product, make sure that the wireless microphone frequency of your Go-Sound 8-10 AMW – or at least one of the two frequencies for Go-Sound AMW 12-15 AMW – is 175MHz)

Plug and play setup

30m ideal distance (without obstacles)

Simple and lightweight bodypack

Lightweight Headset with cardioid electret capsule

Tie Microphone with clip and omni-directional electret capsule

SPECIFICATIONS

| | |
|-------------------------|-----------------------|
| Carrier Frequency | VHF - 175.00MHz |
| Transmitter Power | 10mW |
| Modulation Type | FM |
| Deviation | 37KHz |
| Spurious Emission | > 30dB |
| Continuous Using | 7 hours |
| Frequency Stabilization | Automatic calibration |
| Dynamic Range | > 90dB |

GO-SOUND POCKET MIC KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO- SOUND AMW SPEAKERS

| | |
|---------------------------|-------------------------------------|
| Total Harmonic Distortion | < 0.5% |
| Frequency Response | 40Hz~15KHz ± 3 dB |
| Input Connector | 1/8" mono Jack (without thread) |
| Knobs | Mic Volume |
| LED | Red (battery-low) |
| Battery Voltage | 3V (2x1.5V AA Battery) |
| Headset Microphone | Cardioid electret capsule |
| Headset Connector | 1/8" Mini-Jack (90° without thread) |
| Lavalier Microphone | Omni-directional electret capsule |
| Lavalier Connector | 1/8" Mini-Jack (without thread) |