


## DJM-250-MK2

# 2-CHANNEL MIXER

The DJM-250MK2 has inherited some of the professional features of the popular DJM-900NXS2, such as the Magvel crossfader and Sound Color FX filter. Straightforward controls, a clear layout, and dedicated 3-band isolators let you scratch and mix instinctively. The dithering technology on this mixer results in warm, high-quality audio from both analogue and digital sources. Plus its built-in sound card lets you connect the mixer to your PC/Mac and use rekordbox dj to perform with CDJs. Or hook up the DJM-250MK2 to turntables and use rekordbox dvs in combination with our control vinyl to scratch and mix with digital files stored on your computer.



## DJM-250-MK2

# 2-CHANNEL MIXER

## PRODUCT DETAILS

### KEY FEATURES

Clear layout and Magvel faders

Smooth mixing

Flagship filter FX

Built in USB sound card

Recordbox Dj bundled

Recordbox DVS bundled

High Quality sound

Two headphone outputs

Independent MIC section

Flexible connectivity

### SPECIFICATIONS

<b>DVS Control</b>	rekordbox dvs
<b>Included DJ Software</b>	rekordbox dj, rekordbox dvs
<b>Frequency Range</b>	20 - 20,000 Hz
<b>Sampling Rate</b>	48 kHz
<b>A/D Converter</b>	24 bit
<b>D/A Converter</b>	24 bit
<b>S/N Ratio Line</b>	94 dB
<b>Distortion</b>	< 0.005 % (LINE)
<b>Power Supply</b>	AC adaptor DC 12 V

## DJM-250-MK2

# 2-CHANNEL MIXER

<b>Power Consumption</b>	600 mA
<b>Channels</b>	2
<b>EQ/ISO</b>	3 band
<b>EQ/ISO Range</b>	-8 ~ +6 dB
<b>Sound Color FX</b>	Filter
<b>Inputs</b>	3 LINE (RCA), 2 PHONO (RCA), 1 MIC (1/4 inch TS Jack)
<b>USB</b>	1 USB B port
<b>Outputs</b>	1 MASTER (XLR), 1 MASTER (RCA), 2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)
<b>Included</b>	Power cord, AC adaptor, USB cable, Operating Instructions (Quick Start Guide), License key card
<b>Accessories</b>	(rekordbox dj, rekordbox dvs)