

WF-AA10 WIDEBAND UHF ANTENNA AMPLIFIER

Optimized in the 470 ~ 1000 MHz frequency range, the WF-AA10 offers 12dB (± 1 dB) gain to compensate for signal loss due to long antenna cables, thereby enhancing signal stability and increasing reception range. With an external power supply, the WF-AA10 provides power independently to the internal antenna amplifier. This allows complicated external antenna dividing systems to work efficiently and independently so that longer antenna cables can be connected with more amplifiers. Its aluminum casing provides superb heat dissipation characteristics.



WF-AA10

WIDEBAND UHF ANTENNA AMPLIFIER

PRODUCT DETAILS

SPECIFICATIONS

External Power Input	12÷24V DC (Min. 350mA)
Regulated Supply Output	9V DC (Max. 250mA)
Bandwidth	470MHz ÷ 1000MHz
IIP3: +18dBm	
Gain	+12dB (±1dB)
Noise Index	< 2.5dB
Impedance	50 Ohm
Accessories	1 x AC/DC Adapter, 1 x User manual
Dimensions(WxHxD)	93x26x55mm
Packing Size(WxHxD)	195x60x150mm
Weight	0.17Kg
Packing Weight	0,25Kg