

HSMA-240D PLAY 2U 240W SINGLE-ZONE MIXER AMPLIFIER WITH DAB+/FM/USB/BT

Helvia HSMA / HDMA / HMMA Play Series bring a wide offer of integrated PA Sound Reinforcement solutions with digital amplifiers in class-D with processing, zone number from 1 to 4 with 100V outputs, rated powers between 120W and 350W total*, an overall 4-16? power output and a whole series of features such as DAB+receiver, BT audio streaming, USB player, FM radio, mixer with 1 front Mic input with priority, 3 Mic/Line inputs, +48V Phantom Power, 2 stereo Aux Inputs, Level Attenuators for each zone, EMC input at 100V, auxiliary power supply at +24V DC (only models at 120W and 240W).

In short, these new mixer-amplifiers enclose in 2 standard 19 "units (rack-ear kit included) everything required for a simple and efficient small-to-medium multi-zone installation.































HSMA-240D PLAY 2U 240W SINGLE-ZONE MIXER AMPLIFIER WITH DAB+/FM/USB/BT

PRODUCT DETAILS

KEY FEATURES

1-Zones Operation with Output Attenuator

Class-D Power Amplifiers with 240W RMS power

100V Constant Voltage Zone Output

4-16? Overall Low-Impedance Output (not controlled by zone attenutators)

Built-in High-Efficiency Digital Audio Processing

Advanced Over Current and Overload Protection

DC 24V Auxiliary Power Supply for Emergency Purposes

EMC 100V Emergency Input with Priority

Multimedia Player with OLED Screen and Remote Control

FM, DAB+, BT 5.0, USB Operation

Mixer with Independent Volume Control, Master Level and 2-Band EQ

3 Mic/Line Balanced Inputs with +48V Phantom

1 Front Mic Unbalanced Input with Priority

2 Stereo Line Auxiliary Inputs

SPECIFICATIONS

1 zone

Rated power 240W

Freq. response 100Hz~16KHz

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it



HSMA-240D PLAY 2U 240W SINGLE-ZONE MIXER AMPLIFIER WITH DAB+/FM/USB/BT

Power Outputs 100V for each zone; Overall @ 4-16?

THD ?1%

S/N Ratio ?80dB

N. Channels 4 Mic Inputs, 2x Aux Line Inputs, 1x FM/DAB+/BT/USB Built-In Player

EQ Controls Low (± 6dB @ 150Hz) High (± 6dB @ 10kHz)

AUX Output 1000mV

AUX 1-2 Inputs 300mV

MIC 1 Input 15mV ±3mV

MIC/Line 2/3/4 Inputs 30mV ±3mV (Mic Position); 300mV (Line Position)

EMC input 100V

BT 5.0 Version with EDR (10m receiving range, without obstacles)

DAB+ 170MHz-240MHz

FM Tuner 88MHz-108MHz

USB Audio Format MP3, WAV, WMA, SBC (FAT32, max. 128GByte)

Main Power AC220-240V, 50Hz/60Hz

Off-Load Consumption 8W

Full-load Consumption 285W

Auxiliary Power DC 24V – 10A max.

Fuse F4AL

Fan Noise Level 38 dB (A-weighted)

Unit Size (WxDxH) 482 x 300 x 88 mm (16.8 x 3.5 x 11.8 in)

Unit Weight 7,05 kg (15.5 lbs.)

Packing Size (WxDxH) 747 x 397 x 164 mm (29.4 x 15.6 x 6.4 in)

Packing Weight 8,55 kg (18.8 lbs.)

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it