


DJM-S11

PROFESSIONAL SCRATCH STYLE 2-CHANNEL DJ MIXER

Raise your game with the DJM-S11. This new professional 2-channel, 4-deck control battle mixer enhances various elements from its predecessor, the DJM-S9, and offers a host of brand-new features to help you perform more freely with Serato DJ Pro or rekordbox.



DJM-S11

PROFESSIONAL SCRATCH STYLE 2-CHANNEL DJ MIXER

PRODUCT DETAILS

KEY FEATURES

A 4.3-inch customizable touch screen

Expanded effects section

Improved Performance Pads

Enhanced MAGVEL FADER PRO

Crystal-clear sound quality

Color: Black

SPECIFICATIONS

2 channels

Frequency range 20 - 20.000 Hz

Power Supply AC 100-240 V, 50 Hz / 60Hz

S/N Ratio USB 115 dB (USB), 105 dB (LINE), 90 dB (PHONO), 80 dB (MIC), 90 dB (AUX)

Distorsion 0.003% (USB), 0.005% (LINE)

Power Consumption 34W

Full assignable MIDI controls

Auto Standby

Compatible DJ Software (not included) Unlocks Serato DJ Pro, rekordbox

DVS Control Unlocks Serato DVS, rekordbox

Level Meter Size 9 segment

DJM-S11

PROFESSIONAL SCRATCH STYLE 2-CHANNEL DJ MIXER

EQ/ISO Range	–8 dB to +6 dB (ISO), –26 dB to +6 dB (EQ)
EQ/ISO	3 band
Reverse Channels	
Peak Limiter	
Sound Color FX	Filter, Dub Echo, Noise, Pitch, Wide Filter
Beat FX	Echo, Ducking Echo, Echo Out, Spiral, Helix, Delay, Reverb, Back Spin, One-shot Spin, Vinyl Brake, One-shot Brake, Flanger, Phaser, HP Filter, LP Filter, Trans, Kill, Roll, Fader Pitch, Fader Synth
Deck 3/4 control	
Effect Sampler	3-Band Isolator, Auto BPM Counter
Magvel Fader Pro Crossfader	
CURVE Assignable, Reverse Crossfader, Tension Adjustment	
Mic.	XLR/Jack Combo da 1/4 di pollice
Talkover Attenuator	
Sound card	USB (Type-B), Sample rate
Inputs	2 LINE (RCA), 2 PHONO (RCA), 1 MIC (XLR & 1/4 inch TRS Jack), 1 AUX (RCA)
USB	2 USB A ports, 2 USB B ports
Outputs	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 2 PHONES (1/4-inch stereo jack, 3.5-mm stereo mini-jack)
Software System Requirements	Visit serato.com for its specifications, Visit rekordbox.com for its specifications
What's in the Box	DJM-S11, Power cord, USB cable, Fader bumper Ax4, Fader bumper Bx2, Warranty (for some regions), Quick Start Guide, Precautions for Use, Serato DJ Pro Expansion Pack voucher
Dimensions (WxHxD)	267x107,9x452,2 mm; Weight