



DJM-S7

**SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER**

This new 2-channel battle mixer gives you the freedom to customize your setup and bring your own unique style to every performance. The unit enables free use of Serato DJ Pro and it's a Hardware Unlock device for rekordbox, so you can use performance features in either application.



DJM-S7

# SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER

## PRODUCT DETAILS

### KEY FEATURES

Magvel Fader Pro

Boosted the rigidity of the knob mounting shaft in the vertical direction by 30% so you can scratch with even more confidence

8 Large performance pads

Large effect levers

Bluetooth input: wirelessly add audio from your phone

Loop MIDI: automated control of Dj software functions

USB hub

MIDI assignable via USB Type-B

Serato Dj Pro

Serato DVS

Pitch'n Time Dj

Recordbox

Colore: Nero

### SPECIFICATIONS

<b>MIDI control</b>	assegnabile
<b>Compatible DJ Software</b>	Unlocks Serato DJ Pro, rekordbox
<b>DVS Control</b>	Unlocks Serato DVS, rekordbox
<b>Bluetooth Audio Input</b>	standard version Bluetooth 5.0; Supported Codecs

## DJM-S7

# SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER

<b>Level Meter Size</b>	9 segment
2 channels	
<b>Frequency Range</b>	20 - 20000 Hz
<b>Power Supply</b>	AC 100-240 V, 50 Hz / 60Hz
<b>S/N Ratio USB</b>	110 dB (USB), 103 dB (LINE), 88 dB (PHONO), 80 dB (MIC), 103 dB (AUX)
<b>Distortion</b>	0.003% (USB), 0.005% (LINE)
<b>Power Consumption</b>	24W
<b>EQ/ISO</b>	3 band
<b>EQ/ISO Range</b>	-8 dB to +6 dB
Reverse Channels	
Peak Limiter	
Auto BPM Counter	
<b>Crossfader</b>	Magvel Fader Pro, CURVE Assignable, Reverse Crossfader, Tension Adjustment
<b>Mic Connection</b>	XLR / 1/4-inch Jack Combo with Talkover Attenuator
<b>Sound card</b>	Connection USB (Type-B), Sample Rate 24 bit, Frequency 48 kHz
<b>Inputs</b>	2 LINE (RCA), 2 PHONO (RCA), 1 MIC (XLR & 1/4 inch TRS Jack), 1 AUX (RCA)
<b>USB</b>	2 USB A ports, 2 USB B ports,
<b>Outputs</b>	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 2 PHONES (1/4-inch stereo jack, 3.5-mm stereo mini-jack)
<b>Sound Color FX</b>	Filter, Dub Echo, Noise, Pitch, Wide Filter
<b>Beat FX</b>	Echo, Ducking Echo, Echo Out, Spiral, Helix, Delay, Reverb, Back Spin, One-shot Spin, Vinyl Brake, One-shot Brake, Flanger, Phaser, HP Filter, LP Filter, Trans, Kill, Roll, Fader Pitch, Fader Synth
<b>Software System Requirements</b>	Visit <a href="http://serato.com">serato.com</a> for its specifications; Visit <a href="http://rekordbox.com">rekordbox.com</a> for its specifications