

WF-V11PC

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (205.75 MHZ)

WF-V11 is the answer to all those who need a reliable, high-quality sound, and easy to use wireless microphone system. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V11 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.



WF-V11PC

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (205.75 MHZ)

PRODUCT DETAILS

KEY FEATURES

VHF Transmission with SMD Technology

4 available Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

Strong yet lightweight bodypack transmitter

Professional and Lightweight Headset with high-sensibility dynamic cardioid capsule

SPECIFICATIONS

Carrier Frequency	VHF 200 - 215.3 MHz
Operating Frequency	205.75 MHz
Frequency Stabilization	Automatic calibration
Dynamic Range	> 90dB
Total Harmonic Distortion	< 0.5%
Frequency Response	40Hz - 16kHz / ± 3 dB
Packing Dimensions (WxHxD)	436 x 104 x 324 mm
Packing Gross Weight	2.0 kg
Receiver Power Supply	DC12V, 500mA
Receiver Consumption	< 2W
Signal/Noise Ratio	> 95dB

WF-V11PC

VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (205.75 MHZ)

Receiving Sensitivity	10dBuV
De-Emphasis	75uS
Audio Output Level	Balanced 400mV; Unbalanced 400mV
Receiver Size (WxHxD)	211 x 43 x 115 mm (antennas not incl.)
Antenna Length	110 mm (min.) 430 mm (max.)
Net Weight	0.295 kg
Transmitter Power	10mW
Modulation Type	FM
Deviation	37KHz
Battery Voltage	3V (2x1.5V AA-Type Batteries)
Continuous Using	7 hours
Pocket Trans. Dimensions (WxHxD)	62 x 103 x 30 mm
Antenna (W/DxH)	Ø3 x 9 mm
Pocket Transmitter Net Weight	0.132 kg (batteries included)